

M-120 PLUS

MULTI STANDARD PROGRAMMABLE CB MOBILE TRANSCEIVER

M-120 PLUS MULTI STANDARD PROGRAMMABLE CB MOBILE TRANSCEIVER

State-of-the-art Citizen Band 27MHz mobile transceiver, with advanced hardware and software design, suitable for Citizen Band operators and for car & truck drivers. 9 bands programmable multi standard circuit design, matching the frequency & operating mode requirements of all the European countries. 3-digit LED channel/band indicator, 3W speaker for strong and clear audio sound, fixed or manual Squelch control and Automatic Noise Limiter. New soft type microphone curl cord. Compact sized easy to install cabinet. One radio only, ready for use in all the European countries !

**MULTI STANDARD
PROGRAMMABLE
TECHNOLOGY**

**NEW EXTRA SOFT
MICROPHONE
CURL CORD**



9 BANDS

**3-DIGIT
LED DISPLAY**

ANL

**3W
SPEAKER**

**SQUELCH +
AS SQUELCH**

**EMG
CH9/19**

**QUICK UP
QUICK DOWN**

**4-PIN MIC
CONNECTOR**

feature
PACKED
see reverse for full details



INTEK®

M-120 PLUS

MULTI STANDARD PROGRAMMABLE CB MOBILE TRANSCEIVER

State-of-the-art CB (27 MHz) mobile transceiver,
with advanced software & hardware design,
specifically conceived for Citizen Band operators and for truck / car drivers

One radio only, ready for use in all the European countries !

Main features :

- MULTI STANDARD CIRCUIT DESIGN
- 3-DIGIT BAND / CHANNEL DISPLAY
- 9 BANDS PROGRAMMABLE
- AM / FM
- 3-DIGIT BAND / CHANNEL DISPLAY
- FIXED OR MANUAL SQUELCH
- HIGH QUALITY CONDENSER MICROPHONE WITH 4-PIN RING CONNECTOR
- TX LED INDICATOR
- RX LED INDICATOR
- ANL AUTOMATIC NOISE LIMITER
- QUICK UP / DN CH SELECTION
- EMERGENCY CHANNELS CH9 / CH19
- RUBBER SOFT TOUCH KEYS
- 3W SPEAKER

AM / FM MODE
It selects the operating mode AM/FM (only if allowed by the programmed band).

CH9 / CH19
Three position switch selects the two emergency channels (CH9 or CH19) or the normal operating channels.

TX LED
Red LED confirms if transceiver is in transmitting mode.

RX LED
Green LED confirms if transceiver is in receiving mode.

DISPLAY
3-Digit LED display shows the selected band and the operating channel.



CONDENSER MICROPHONE
High quality condenser microphone.

OFF / VOL
OFF / Volume control knob.

AS / SQUELCH
Dual mode fixed or manual squelch control knob.

Channel UP / Channel DN
These keys select the operating channel and they include the "quick" selection function.



ELECTRET MICROPHONE
High quality condenser microphone, with 4-pin ring connector and soft type curl cord.

NEW EXTRA SOFT MICROPHONE CURL CORD

MULTI STANDARD PROGRAMMABLE TECHNOLOGY

RoHS
2002/95/EC

SPECIFICATIONS

GENERAL

Channels Refer to programmed band
Modes (AM, FM) Refer to programmed band
Operating Temp. -10°/+55°C
DC Input Voltage 13.2Vdc ±15%
Size 140(L) x 37(H) x 190(D) mm
Weight 750 gr.

RECEIVER

System CPU Controlled Double Conversion Super Heterodyne
IF 1° 10.695 MHz / 2° 455 KHz
Sensitivity 0.5µV for 20dB SINAD (FM)
0.5µV for 20dB SINAD (AM)
Audio Output Power @10% THD 2.5W at 8 Ohm
Audio Distorsion <8% at 1 KHz
Image Rejection 65dB
Adjacent Ch. Rejec. 65dB
Signal/Noise Ratio 45dB
Current Drain 350mA (stand-by)

TRANSMITTER

System CPU Controlled PLL Synthesizer
Max Output Power 4W at 13.2Vdc
Modulation AM (from 85% to 90%)
FM (1.8 KHz ±0.2 KHz)
Output Impedanced 50 Ohm unbalanced
Current Drain 1300 mA (at no modulation)

FREQUENCY BAND / MODE PROGRAM

E1 ITALY/SPAIN 40CH AM/FM 4W
I2 ITALY 36CH AM / FM 4W
dE GERMANY 80CH FM 4W / 12CH AM 1W
d2 GERMANY 40CH FM 4W / 12CH AM 1W
EU EUROPE/France 40CH FM 4W / 40CH AM 1W
CE CEPT 40CH FM 4W (DEFAULT)
U ENGLAND 40CH + CEPT 40CH FM 4W
PL POLAND 40CH AM/FM 4W (-5 KHz)
Pd POLAND 40CH AM 1W / FM 4W (-5 KHz)

IMPORTANT ! This 27 MHz CB transceiver has been factory pre-programmed on the CE frequency band (CEPT 40CH FM 4W). This product is subject to national restrictions. Before operating this radio, please check that the frequency band has been correctly programmed according to the country where radio is used. Please read carefully the instruction manual before using this product.




RECOMMENDED BY INTEK !

**LEADER IN CB 27 MHz
CAR & TRUCK MOBILE ANTENNA**

RECOMMENDED BY INTEK !



**LEADER IN CB 27 MHz
CAR & TRUCK MOBILE ANTENNA**



CE 0678 CH



INTEK